



LED Fountain Light Kits

12V, Single Phase



Operation

- ⇒ Photo eye built into each Kasco power control panel registers levels of darkness and allows 120V power to flow to the low voltage transformer when dark.
- ⇒ Low voltage transformer takes in 120V and produces 12V power to illuminate the 42 LED bulbs.
- ⇒ Light from the LED bulbs shines onto the fountain pattern and illuminates the water.
- ⇒ When the fountain turns off or it becomes light out, power will stop flowing to the low voltage transformer and the lights will shut off.

Quick Facts

- ⇒ Complete Package includes Potted 42 Light LED Ring with Thermoplastic Housing, and SJTOW 3 Wire Power Cable with Built-In Low Voltage Transformer
- ⇒ Potted LED Lights for Leak Proof Operation
- ⇒ 100,000 Hour Rated LED Lights
- ⇒ Amber Colored Lights
- ⇒ Total Component Listed by ETL to meet UL and CSA Standards for Use on Floating Fountains
- ⇒ 2 Year Warranty
- ⇒ UPS Shippable
- ⇒ Made in the USA
- ⇒ Energy Efficient, Low Voltage Lighting
- ⇒ Industrial Strength Design
- ⇒ 12 Watt Fixture

Light Kit Model

L140

- ⇒ 1 Potted 42 Light LED Ring with Thermoplastic Housing
- ⇒ 100,000 Hour Rated
- ⇒ Includes Low Voltage Transformer
- ⇒ Available in 50', 16 Gauge Cord
- ⇒ Used with 1400JF Aerating Fountain Models
- ⇒ Amber Colored Lights



The light ring attaches to the float using stainless steel hardware for a secure assembly. The light ring can be easily added after original purchase.

Kasco LED Lighting Package Specifications

Model #	Cord Length	Number of Fixtures	Voltage/Phase/Hz	Wattage Per Fixture	Total Wattage	Lens Position	Shipping Weight	Number of Boxes
L140	50'	1	12/1/60	12	12	Above Water	5 Lbs.	1

Kasco Marine, Inc.
800 Deere Rd.
Prescott, WI 54021

Ph: (715) 262-4488 * Fax: (715) 262-4487
www.KascoMarine.com * www.GotAlgae.com
Sales@KascoMarine.com



Rev. 9/5/07