

C-25 TIMER CONTROL INSTRUCTIONS

Portable Timer with Ground Fault Interrupter

(UNIT: 9.8 FLA, 58.8 LRA 120 VAC

LIGHT: 300 W, 120 VAC)

IMPORTANT

This portable timer is designed for CONTROLLING the connected equipment only. Unplug timer before servicing the unit or the equipment it controls. **THIS SWITCH IS NOT TO BE USED AS A POWER DISCONNECT!** For maximum protection against electrical shock hazard, perform test procedure on G.F.C.I. at least once a month. Mount at least 5 ft. from open water.

G.F.C.I. TEST PROCEDURE

The G.F.C.I. should be checked every month to make sure that it is operating properly. Just follow the simple instruction below. It is recommended to maintain a maintenance diary of your monthly safety check.

1. Push TEST button, RESET button should pop out from inner surface. This should result in power being OFF at the outlet protected by the G.F.C.I. Verify by plugging test lamp into the outlet. Be sure the timer is in the ON position.
2. If the G.F.C.I. tests okay, restore power by pushing the RESET button back in. THE RESET BUTTON MUST BE PUSHED FIRMLY AND FULLY INTO PLACE UNTIL IT LOCKS AND REMAINS DEPRESSED AFTER PRESSURE HAS BEEN REMOVED.

DANGER: IF RESET BUTTON DOES NOT POP OUT, IF TEST LAMP REMAINS LIT WHEN RESET BUTTON DOES POP OUT, OR IF THE G.F.C.I. FAILS TO RESET PROPERLY, DO NOT USE TIMER! CONTACT A QUALIFIED SERVICE TECHNICIAN!

Failure to use the C-25 with Kasco fountains will void the warranty and cause the fountain to not be listed to UL and CSA standards via ETL.

UNDER NO CIRCUMSTANCES SHOULD ANYONE ENTER THE WATER WHEN A UNIT IS IN OPERATION.

TIMER-OPERATING INSTRUCTIONS

C-25 Control box will turn the aerator/fountain **ON & OFF** with the Timer. Kasco lights will turn **ON** with the Photo Eye and **OFF** with Timer. C-25 Control box is to be used with Kasco Approved Lights **ONLY!**

1. Insert “**ON**” (GREEN) and “**OFF**” (RED) trippers into dial at desired ON and OFF times.
2. Turn dial clockwise one or more revolutions until correct time-of-day (AM or PM) in window is aligned with arrow.
3. Plug aerator/fountain cord into the **RIGHT** hand outlet (labeled **PUMP**).
4. Plug transformer cord into **LEFT** hand outlet (labeled **LIGHT**).
5. Set Transformer Timer dial to be **ON** 24 hours per day. (Lights will then run on the Photo Eye on C-25.)

FOR TEMPORARY MANUAL OPERATION

Rotate **MANUAL** knob counter-clockwise (←) to desired **ON** or **OFF** position. Timer will follow next automatic operation.



KASCO MARINE, INC., 800 Deere Road
Prescott, WI 54021-1241 * Phone (715) 262-4488